



FAME

MILD TO MODERATE HEARING LOSS

- Stable class D circuit
- Wheel volume control
- N/H for program switch
- Low battery warning Indicator
- Earhook and thin tube open fit optional
- Streamlined design make you comfortable
- Stay dry and easy to clean

TECHNICAL SPECIFICATIONS

FAME		
Measurement	ANSI/IEC 2cc Coupler	IEC OES Coupler
Peak OSPL90 (dB SPL)	115	119
HFA OSPL90 (dB SPL)	105	NA
RTF OSPL90 (dB SPL)	NA	100
Peak Gain (dB)	54	56
HFA Full-On Gain (dB)	50	NA
RTF Full-On Gain (dB)	NA	44
Frequency Range (Hz)	200- 4500	200- 4500
Reference Test Frequency (kHz)	NA	1.6
HFA Frequencies (kHz)	1.0, 1.6, 2.5	NA
Reference Test Gain (dB)	45	50
EIN Level (dBSPL)	<20	<20
Harmonic Distortion 500 Hz (%)	<3	<3
800 Hz (%)	<2	<2
1600 Hz (%)	<1	<1
Induction Coil Sensitivity		
HFA SPLITS (ANSI) (dB SPL)	92	NA
MASL (IEC) (dB SPL)	NA	97
ANSI/IEC Battery Current (mA)	1.31	1.31
Idle Current (mA)	1.27	1.27
Estimated Battery Life for 16-Hour Day		
13 Zinc Air (days)	15	15