



## RADIUS 16

### BEHIND THE EAR HEARING AID DIGITAL PROGRAMMABLE

- 100% Digital Signal Processing
- 4 User Program
- Adaptive Feedback Canceller
- 16 Channels & 32 Bands
- Push Button volume control
- Streamlined design make you comfortable
- Stay dry and easy to clean

## TECHNICAL SPECIFICATIONS

### BEHIND THE EAR HEARING AID DIGITAL PROGRAMMABLE

## RADIUS 16

Max OSPL 90 (dB SPL)	125.1 - 135 dB
HF Average OSPL 90 (dB SPL)	125.1 - 135 dB
HF Average- Full On Gain (at 50/60 dB Input)	60 dB (min.)
<b>Frequency Range (Hz)</b>	200-4500 Hz
<b>EIN Level (dBSPL)</b>	<30
<b>Harmonic Distortion</b> 500 Hz (%)	<7
800 Hz (%)	<7
1600 Hz (%)	<7
<b>Induction Coil Sensitivity</b>	75 dB (min.)
Battery Current (mA)	<5 mA
Battery Size (Zinc Air)	13



IS :16127



CM/L - 8800111109

**MAKE IN INDIA**

## Earkart Private Limited

A - 133, Ground Floor, Block A  
Sector 63, Noida - 201301, India.  
Contact No : 0120 4102857  
www.earkart.in