



RADIUS

BEHIND THE EAR HEARING AID DIGITAL PROGRAMMABLE

- 100% Digital Signal Processing
- 3 User Program (min.)
- Adaptive Feedback Canceller
- 4 Channels (min.) & 4 Bands (min.)
- Push Button volume control
- Streamlined design make you comfortable
- Stay dry and easy to clean

TECHNICAL SPECIFICATIONS

BEHIND THE EAR HEARING AID DIGITAL PROGRAMMABLE

RADIUS

Max OSPL 90 (dB SPL)	125.1 - 135 dB
HF Average OSPL 90 (dB SPL)	125.1 - 135 dB
HF Average- Full On Gain (at 50/60 dB Input)	60 dB (min.)
Frequency Range (Hz)	200-4500 Hz
EIN Level (dBSPL)	<30
Harmonic Distortion 500 Hz (%)	<7
800 Hz (%)	<7
1600 Hz (%)	<7
Induction Coil Sensitivity	75 dB (min.)
Battery Current (mA)	< 5 mA
Battery Size (Zinc Air)	13

IS :16127



CM/L - 8800111109

MAKE IN INDIA

Earkart Private Limited

A - 133, Ground Floor, Block A
Sector 63, Noida - 201301, India.
Contact No : 0120 4102857
www.earkart.in