



## RADIUS 12

MODEL NO. RA12331

### BEHIND THE EAR HEARING AID DIGITAL PROGRAMMABLE

- 100% Digital Signal Processing
- 2 User Program
- Adaptive Feedback Canceller
- 12 - 16 Channels
- Push Button volume control
- Streamlined design make you comfortable
- Stay dry and easy to clean

## TECHNICAL SPECIFICATIONS

### BEHIND THE EAR HEARING AID DIGITAL PROGRAMMABLE

## RADIUS 12

Max OSPL 90 (dB SPL)	105 - 135 dB
HF Average OSPL 90 (dB SPL)	100 - 135 dB
HF Average- Full On Gain (at 50/60 dB Input)	40 dB (min.)
<b>Frequency Range (Hz)</b>	200-4500 Hz
<b>EIN Level (dBSPL)</b>	<30
<b>Harmonic Distortion</b> 500 Hz (%)	<7
800 Hz (%)	<7
1600 Hz (%)	<7
<b>Induction Coil Sensitivity</b>	75 dB (min.)
Battery Current (mA)	<5 mA
Battery Size (Zinc Air)	13

IS :16127



CM/L - 8800111109

**MAKE IN INDIA**

## Earkart Private Limited

A - 133, Ground Floor, Block A  
Sector 63, Noida - 201301, India.

Contact No : 0120 4102857

[www.earkart.in](http://www.earkart.in)